

COPY

1

Copy

EXPRESS MAIL NO.: EL 067 094 954 US

Nokia Mobile Phones Limited Docket No.: NC12848
Perman & Green, LLP Docket No.: 490P007306-US (PAR)
Patent Application Papers of: Seppo Alanärä

5 **METHOD AND APPARATUS FOR TRANSMITTING DTX_LOW STATE
 INFORMATION FROM MOBILE STATION TO BASE STATION**

**CLAIM OF PRIORITY FROM A COPENDING PROVISIONAL PATENT
APPLICATION:**

10 Priority is herewith claimed under 35 U.S.C. §119(e) from
 copending Provisional Patent Application 60/051,716, filed
 July 3, 1997, entitled "Method and Apparatus for
 Transmitting DTX low state Information From Mobile Station
 to Base Station", by Seppo Alanärä. The disclosure of this
15 Provisional Patent Application is incorporated by reference
 herein in its entirety.

FIELD OF THE INVENTION:

This invention relates generally to radiotelephones and, in
particular, to radiotelephones or mobile stations such as
those capable of operation with a cellular network.

20 **BACKGROUND OF THE INVENTION:**

Figures 3A-3C depict the frame, normal reverse link slot
format, and abbreviated reverse link slot format,
respectively, for an exemplary prior art digital Time
Division Multiple Access (TDMA) cellular air interface
25 known in the art as IS-136 (see, for example, Section 4.4
 of IS-136.1, Rev. A, 3/21/96 and IS-136.2, Rev. A,
 2/12/1996). The reverse link is considered to be in the
 direction from a mobile station (MS) to a base station
 (BS), which forms a part of a Base Station/Mobile Switching
30 Center/Interworking function (BMI).

Fig. 3A shows that a 40 millisecond frame consists of six time slots. Slots 1-3 and 4-6 each comprise one TDMA Block. In the reverse direction from the mobile station to the base station, which is a case of most interest to this invention, the frames may be continuously transmitted. A given mobile station is assigned to transmit in one slot per frame for a half data rate case, and is assigned to transmit in two time slots for a full data rate case.

Fig. 1B illustrates one time slot of a Digital Control Channel (DCCH) that is transmitted to the BMI on a reverse channel. The slot starts with a bit guard (G) field, a six bit ramp (R) field, a 16-bit preamble (PREAM) field, and a 28-bit (14 symbol) SYNC word/time slot identifier field. The SYNC word/time slot identifier field is used for slot synchronization, equalizer training, and time slot identification. These fields are followed by two 122-bit DATA fields separated by an additional synchronization field (i.e., the 24-bit SYNC+ field).

Fig. 1C illustrates one abbreviated time slot of the Digital Control Channel (DCCH) that is transmitted to the BMI on a reverse channel. It can be noted that the second data field is shortened to 78-bits, and a 44-bit abbreviated guard (AG) field is added during which time the mobile station maintains a carrier off condition.

IS-136.1, Rev. A, describes in Section 4.4.3.1 a channel encoding technique, in Section 4.4.3.2 an intraburst interleaving technique for the DATA fields, and in Section 4.4.3.2.2 an interleaving scheme and algorithm for transmitting the encoded data bits of the DATA fields in the normal length burst case of Fig. 1B, and the abbreviated length burst case of Fig. 1C.

Many modern digital cellular communications systems,

including IS-136, support a Discontinuous-Transmission (DTX) mode of operation wherein the mobile station transmitter autonomously switches between two transmitter power levels while the mobile station is in a conversation state. By example, the mobile station can enter a DTX_Low power state during a pause in speech, thereby conserving battery power. In the IS-136 system DTX operation can be initiated by the mobile station when on either an analog voice channel or a digital traffic channel, if permitted by the base station in broadcast control channel signalling.

While in the DTX low power state the mobile station may still be required to periodically send channel quality measurements taken on adjacent base stations as a part of a Mobile Assisted Handoff (MAHO) operation. Reference in this regard can be had generally to IS-136.2, Rev. A, Section 2.4.5, and in particular to Section 2.4.5.3 "MAHO Operations with DTX Operation".

Also while in the DTX low power transmitter state the BMI generates so-called "comfort noise" (CN) based on comfort noise parameters that are received from the mobile station. The use of comfort noise insures that the called party will hear a background noise component that is consistent with a normal conversation, as opposed to a complete and unnatural cessation of background noise due to the transmitting mobile station's transmitter being turned off or substantially reduced in power.

If the base station requires, the mobile station may not ramp down to the lowest possible transmitter power level, but may instead maintain a predefined minimum transmitter power such that adjacent base stations are able to use so-called digital locate receivers to monitor the mobile station's transmissions for power measurement and/or other purposes. In true DTX, the mobile station can completely

terminate transmissions, thereby conserving a maximum amount of mobile station power.

However, the system specification defined in IS-136.1 and IS-136.2 does not include any definitive way for the mobile station to indicate to the BMI the beginning of the DTX mode. As a result, a decoder in the BMI cannot readily determine whether to employ bad frame masking because of lost slots due to fading (See IS-136.2, Section 2.2.2.2.3.2), or whether to generate comfort noise based on CN parameters. In addition, the BMI cannot locate the so-called hang-over slots, on which the BMI computes basic parameters for the background noise. The location of the hangover slots is important, since if the BMI does not receive the comfort noise parameters in the beginning of the slot, it must use the previously derived comfort noise until the next comfort noise parameters are received.

Due to the above-mentioned interleaving, the data bits of a last slot that is transmitted before entering the DTX_Low State have been unused. Currently in IS-136 a two slot interleaving technique is used (see IS-136.2, Figure 2.1.3.3.3.2-1 and Section 2.1.3.3.4), which leaves 130 bits (half of a 260 bit slot) unused in the last slot. The last slot transmitted is typically a Fast Associated Control Channel (FACCH) slot, which is defined as a blank-and-burst channel used for signalling exchange between the mobile station and the base station.

It has been proposed in IS-136 (see contribution TR45.3.5/97.03.25.04) that a 68-bit truncated slot be used as a transmit (TX) slot when the mobile station is in the DTX_Low State. A revised contribution in this regard is TR45.3.6/97.06.10. Comfort Noise parameters have been proposed to be carried as FACCH messages on the FACCH channel.

In the existing Global System for Mobile Communication (GSM) DTX operation, the entry to the DTX mode is indicated by CN parameters sent with inband signaling. However, if for some reason this inband signalling is not received, the BMI will execute the bad frame masking procedure that repeats previous speech frames. In IS-136 the CN parameters are sent as FACCH messages, and similarly if the BMI fails to receive the CN parameters, or some other indication of the mobile station's entry to the DTX mode, the BMI will enter the bad frame masking procedure (see IS-136.2, Section 2.2.2.2.3.2).

As can be appreciated, the failure by the BMI to determine when the mobile station has entered the DTX mode can result in an objectionable audible signal being generated due to the repeating of the last received (good) speech frame.

A further existing problem of the DTX mode as currently specified relates to the number of slots that must be sent from the mobile station to the BMI while the mobile station is in the DTX_Low State. These slots are used, typically, for sending the CN parameters.

OBJECTS AND ADVANTAGES OF THE INVENTION:

It is an object and an advantage of this invention to provide an improved method for transitioning a mobile station and BMI into the DTX mode of operation.

It is a further object and an advantage of this invention to provide an improved method for operating a mobile station and a BMI in the DTX mode of operation.

It is another object and advantage of this invention to provide a method to send Comfort Noise parameters from the mobile station to the base station without incurring

additional transmitter load, over the load required for the transmission of Mobile Assisted Handoff (MAHO) measurements (Channel Quality) information.

SUMMARY OF THE INVENTION

- 5 The foregoing and other problems are overcome and the objects and advantages are realized by methods and apparatus in accordance with embodiments of this invention.

10 A method of this invention is disclosed for operating a mobile station, and includes the steps of, prior to transmitting a burst in a last frame before entering a discontinuous transmission (DTX) mode, generating a message word that indicates that the mobile station is about to enter the DTX mode. In one embodiment the method further includes the steps of using a predetermined generator polynomial to produce an error detection word from the message word; combining the message word and the error detection word into a DTX Trailer word; and convolutionally encoding the DTX Trailer word. The method further includes the steps of interleaving the DTX Trailer word with unused bits of slot containing a speech or a signalling word; and transmitting the interleaved DTX Trailer word to the BMI.

25 In a presently preferred embodiment of this invention the message word has a length of eight bits, the error detection word is an eight bit CRC that is appended to the message word to form the DTX Trailer word, and the DTX Trailer word is error protected using a rate 1/8 convolutional encoder.

30 In other embodiments the message word can be represented by predetermined bits, and is transmitted without being convolutionally encoded or error protected.

Further in accordance with this invention the method provides a technique to send information, such as control information, from the mobile station to the base station by employing unused channel capacity, due to interleaving, when transitioning from the DTX_High state to the DTX-Low state (or vice versa).

In accordance with a presently preferred embodiment of this invention the mobile station periodically combines a Comfort Noise Parameter message with a Channel Quality Measurement message and transmits, over a FACCH, the combined messages from the mobile station to the base station while in the DTX_Low state.

When in the DTX_Low state, the mobile station may periodically transmit an Abbreviated Slot to the base station at intervals specified by the base station. The base station may vary the interval between transmissions, or may command the mobile station to terminate the transmission of Abbreviated Slots.

This invention further teaches a method for operating a mobile station in a circuit switched mode, comprising the steps of (a) generating a data word, such as keystroke data entered by a user; and (b) transmitting the data word, using an unused portion of a slot containing an interleaved signalling word, by interleaving the data word with the signalling word. In one embodiment the signalling word conveys radio channel measurement information from the mobile station to the base station.

Also disclosed is a method for operating a mobile station that includes the steps of, (a) prior to entering a discontinuous transmission (DTX) mode low power (DTX_Low) state, transmitting a Comfort Noise Block, without interruption, and all pending Fast Associated Control

Channel (FACCH) messages from the mobile station to the base station; (b) entering the DTX_Low state; and (c) when in the DTX_Low state, periodically transmitting an Abbreviated Slot to the base station at intervals specified by the base station.

BRIEF DESCRIPTION OF THE DRAWINGS

The above set forth and other features of the invention are made more apparent in the ensuing Detailed Description of the Invention when read in conjunction with the attached Drawings, wherein:

Fig. 1 is a block diagram of a mobile station that is constructed and operated in accordance with this invention;

Fig. 2 is an elevational view of the mobile station shown in Fig. 1, and which further illustrates a cellular communication system to which the mobile station is bidirectionally coupled through wireless RF links;

Figs. 3A-3C depict the frame, normal reverse link slot format, and abbreviated reverse link slot format, respectively, for an exemplary prior art digital TDMA cellular air interface;

Fig. 3D depicts the format of a DTX Trailer Word in accordance with this invention;

Fig. 4 illustrates a DTX Trailer Interleaving technique in accordance with an embodiment of this invention;

Fig. 5 is a block diagram of a 1/8 rate convolutional encoder used by the method of this invention to encode DTX Trailer Words; and

Fig. 6 is a logic flow diagram that illustrates a method in accordance with this invention.

DETAILED DESCRIPTION OF THE INVENTION

Before describing this invention in detail, reference is first made to Figs. 1 and 2 for illustrating a wireless user terminal or mobile station 10, such as but not limited to a cellular radiotelephone or a personal communicator, that is suitable for practicing this invention. The mobile station 10 includes an antenna 12 for transmitting signals to and for receiving signals from a base site or base station 30. The base station 30 is a part of a cellular network comprising the Base Station/Mobile Switching Center/Interworking function (BMI) 32 that includes a mobile switching center (MSC) 34. The MSC 34 provides a connection to landline trunks when the mobile station 10 is involved in a call.

The mobile station includes a modulator (MOD) 14A, a transmitter 14, a receiver 16, a demodulator (DEMOM) 16A, and a controller 18 that provides signals to and receives signals from the transmitter 14 and receiver 16, respectively. These signals include signalling information in accordance with the air interface standard of the applicable cellular system, and also user speech and/or user generated data. The air interface standard is assumed for this invention to include a physical and logical frame structure of a type that was described above, although the teaching of this invention is not intended to be limited only to this specific structure, or for use only with an IS-136 compatible mobile station, or for use only in TDMA or analog/TDMA type systems. The mobile station 10 is assumed to be capable of operating in the DTX mode, and the BMI 32 is assumed to be capable of generating comfort noise and otherwise accommodating the DTX mode of operation of

the mobile station 10. The comfort noise is generated based on comfort noise parameters transmitted to the base station 30 from the mobile station 10, as described in detail below.

5 It is understood that the controller 18 also includes the circuitry required for implementing the audio and logic functions of the mobile station. By example, the controller 18 may be comprised of a digital signal processor device, a microprocessor device, and various analog to digital
10 converters, digital to analog converters, and other support circuits. The control and signal processing functions of the mobile station are allocated between these devices according to their respective capabilities. The controller 18 thus also includes the functionality to convolutionally
15 encode and interleave message and data prior to modulation and transmission.

A user interface includes a conventional earphone or speaker 17, a conventional microphone 19, a display 20, and a user input device, typically a keypad 22, all of which
20 are coupled to the controller 18. The keypad 22 includes the conventional numeric (0-9) and related keys (#,*) 22a, and other keys 22b used for operating the mobile station 10. These other keys 22b may include, by example, a SEND key, various menu scrolling and soft keys, and a PWR key.
25 The mobile station 10 also includes a battery 26 for powering the various circuits that are required to operate the mobile station.

The mobile station 10 also includes various memories, shown collectively as the memory 24, wherein are stored a
30 plurality of constants and variables that are used by the controller 18 during the operation of the mobile station. For example, the memory 24 stores the values of various cellular system parameters and the number assignment module

(NAM). An operating program for controlling the operation of controller 18 is also stored in the memory 24 (typically in a ROM device). The memory 24 may also store data, including user messages, that is received from the BMI 32 prior to the display of the messages to the user.

It should be understood that the mobile station 10 can be a vehicle mounted or a handheld device. It should further be appreciated that the mobile station 10 can be capable of operating with one or more air interface standards, modulation types, and access types. By example, the mobile station may be capable of operating with any of a number of other standards besides IS-136, and the teaching of this invention is not to be construed to be limited to any one particular type of mobile station or air interface standard.

The operating program in the memory 24 may include routines to present messages and message-related functions to the user on the display 20, typically as various menu items. The memory 24 also includes routines for implementing the methods described below.

This invention teaches, in a first aspect, a method for enhancing the DTX operation of a mobile station operated in a cellular network, in which an interleaving of data in slots is used in a traffic channel communication.

Briefly, when the mobile station 10 enters the DTX state, a previously unused portion of the last slot (due to interleaving) is used for indicating to the BMI 32 that the mobile station 10 is about transfer to the DTX state.

Furthermore, the previously unused portion of the last slot can be used by the mobile station 10 to inform the BMI 32 of information regarding the DTX mode, such as a version of

a preferred CN generation process.

Also, the interleaving of the free portion of a slot can be changed from an already specified interleaving scheme.

In addition, information transmitted from the BMI 32 can be used to set the DTX mode of the mobile station. The DTX mode can be one of, by example, true DTX (transmitter off), skip four slots, or skip 16 slots and send a truncated burst in every assigned slot. That is, the mobile station 10 can be set to use truncated slots at every assigned slot, or at a predetermined rate, or can be prohibited from sending any truncated slots (true DTX mode).

To make the channel coding of the free portion of the last slot more resistive to channel errors, a 1/8 rate convolutional coding technique can be employed by the controller 18. This results in a payload of eight bits for CRC and eight data bits. While the channel is currently designed for a Bit Error Rate (BER) value of 3%, a 6% BER performance requirement implies the use of at least 1/8 rate channel coding using eight polynomials (i.e. four additional polynomials over the currently specified FACCH convolutional coding polynomials. The use of eight data bits allows 256 codes to be sent from mobile station 10 to the BMI 32. In accordance with an aspect of this invention, one of these codes can be dedicated to provide a definitive indication to the BMI 32 of the start of the DTX mode, and one or more of the remaining codes can be used to dynamically alter the truncated burst mode.

It is within the scope of this invention to indicate the start of DTX without using a CRC, and to instead use a known bit pattern, such as a channel coded with 1/2 rate convolutional encoding. One example of 1/2 rate convolutional coding is used for speech in IS-136.2. It is,

however, possible to use the known bit pattern w
channel coding, and to then specify a maximum number of bit
errors to allow operation with a noisy radio channel.

For example, in an embodiment of this invention the free
5 bit portion is used in conjunction with 1/2 rate, or 1/4
rate, or even no channel coding. At the BMI base station
receiver the decoded 65 bits, or 32 bits, or 130 bits,
respectively, are then compared to a known bit pattern, and
an erroneous bit count is used to indicate whether what was
10 received was a bad partial frame, or an indication of a
change to the DTX mode. The bit error limit can be based
on channel simulations.

It should be appreciated that the teachings of this
invention can be applied, with suitable modifications, as
15 well to GSM-based systems, wherein interleaving is
performed over four slots.

In further detail, this invention provides in a first
aspect a novel data stream format for the unused portion
(130 bits) of the last TDMA slot before entering the
20 DTX_Low or a Truncated Burst sending mode of operation.

In accordance with a data stream format of this invention
a DTX Trailer block replaces (is used in place of) the user
information block whenever it is to be transmitted. Each
DTX Trailer block is regarded as one signaling word, and a
25 FACCH message can consist of more than one such word.
Messages that span multiple FACCH words can be interspersed
with one or more transmissions containing user information.

The DTX Trailer is interleaved as FACCH bursts, but using
only the odd numbered 10 bit rows in the last transmission
30 burst. More precisely, the mapping of bits from the two
bursts into bits presented sequentially to the input of the

convolutional decoding process can be either the one used for the FACCH or for the coded speech bits. However, to facilitate the future implementation of new speech coders, it may be preferred to use the FACCH interleaving process, which is not expected to change.

Sequential DTX Trailer bits are numbered 0 to 129 in the order they emerge from a rate 1/4 convolutional encoder, and are placed in the interleaving array using, first, those positions otherwise occupied by coded class 1 speech bits, and in the same order. When all positions normally occupied by coded speech bits have been used, the positions normally used by uncoded speech bits are then used, but in a different order.

Bits 0 to 259 are interleaved according to Fig. 4. The bits are transmitted from the interleaving array of Fig. 4 along rows from left to right, using only odd numbered rows from a current frame alternately with even numbered rows of the previous frame, which may be a similar speech or FACCH block. The even numbered rows of an interleaved FACCH block constructed from the frame are transmitted in the next burst, alternating with odd numbered rows from the following block, which may also be speech or FACCH.

With regard to error detection and a Digital Verification Color Code (DVCC) identifier, the following is noted. The 8-bit CRC is placed after 8 information bits, as is shown in Fig. 3D.

Let $a(X) = \text{message}[0]X^7 + \text{message}[1]X^6 + \dots + \text{message}[7]X^0$.

Message[0] is the most significant bit (see IS-136.2, Section 1.2.5 "Coded Digital Verification Color Code (CDVCC)" and Section 2.1.3.3.3.4 "Convolutional Encoding"), where message[N] is the Nth bit of the message field in a

DTX Trailer word.

The parity polynomial is the remainder of the division of the input polynomial $a(X)$ and the generator polynomial, i.e.:

$$5 \quad (a(X)X^{16})/(X^8+X^5+X^4+X^3+1) = q(X) + (b(X))/(X^8+X^5+X^4+X^3+1)$$

where $q(X)$ is the quotient of the division and $b(X)$ is the remainder. The quotient is discarded and only the parity bits are transmitted. Those skilled in the art may recognize that the generator polynomial is a shortened version of the polynomial used on Analog Voice and Control Channels (see the definition in IS-136.2, Section 3.7.1).

$$10 \quad \begin{aligned} \text{Let } c(X) &= C[0]X^{15} + C[1]X^{14} + C[2]X^{13} + \dots + C[64]X^0 \\ &= \text{message}[0])X^{15} + \dots + (\text{message}[7])X^8 + b(X) \end{aligned}$$

where $\text{message}[N]$ is the Nth bit of the message field in a DTX Trailer word. The coefficients of the polynomial $c(X)$ are fed sequentially to a convolutional encoder 40 (see Fig. 5) in the order $C[0]$, $C[1]$, ... $C[15]$.

In accordance with an aspect of this invention, the DTX Trailer data is error protected by means of a rate 1/8 convolutional code. The coding uses the same start and end bit (tail-biting), instead of extra bits, to avoid the overhead introduced with explicit tail bits.

Referring to Fig. 5, the data bits to be encoded are shifted through a rate 1/8 convolutional coding circuit 40. Each new data bit shifted in results in four parity bits being shifted out of the coder 40, the output bits being designated as $(P1, P2, P3, P4, P5, P6, P7, P8)$. One such bit quadruple is produced as a result of shifting in one new data bit. Each of the four parity bits is a different

logical function of the new data bit and the five data bits previously shifted in. Denoting the new data bit by $D(i)$ and denoting the earlier data bits by $D(i-1)$, $D(i-2)$, $D(i-3)$, $D(i-4)$ and $D(i-5)$, the defining equations for

5 $(P1, P2, P3, P4, P5, P6, P7, P8)$ are as follows:

10 $P1 = D(i) + D(i-1) + D(i-3) + D(i-4) + D(i-5)$
 $P2 = D(i) + D(i-1) + D(i-2) + D(i-5)$
 $P3 = D(i) + D(i-1) + D(i-2) + D(i-3) + D(i-5)$
 $P4 = D(i) + D(i-2) + D(i-4) + D(i-5)$
 $P5 = D(i) + D(i-2) + D(i-3) + D(i-5)$
 $P6 = D(i) + D(i-3) + D(i-4) + D(i-5)$
 $P7 = D(i) + D(i-1) + D(i-2) + D(i-4) + D(i-5)$
 $P8 = D(i) + D(i-1) + D(i-3) + D(i-5)$

where + represents modulo 2 addition (XOR).

15 A memory (MEM) 42 of the channel coder 40 is initialized by the controller 18 with the first six bits according to the following:

$D(i)$ $D(i-1)$ $D(i-2)$ $D(i-3)$ $D(i-4)$ $D(i-5)$
 $C[5]$ $C[4]$ $C[3]$ $C[2]$ $C[1]$ $C[0]$ bits

20 The first bit quadruple $(P1, P2, P3, P4)$ is then generated and extracted. The input bits are then shifted through the coder memory so that bit $C[0]$ shifts out, bit $C[1]$ replaces bit $C[0]$, bit $C[5]$ replaces bit $C[4]$ and a new bit (bit $C[6]$) replaces bit $C[5]$ in $D(i)$. After this shift the
 25 memory 42 content is as follows:

$D(i)$ $D(i-1)$ $D(i-2)$ $D(i-3)$ $D(i-4)$ $D(i-5)$
 $C[6]$ $C[5]$ $C[4]$ $C[3]$ $C[2]$ $C[1]$ bits

Another quadruple $(P1, P2, P3, P4)$ is then extracted and likewise, after every subsequent shift until after 10
 30 shifts, the state of the encoder 40 is as follows:

$D(i)$ $D(i-1)$ $D(i-2)$ $D(i-3)$ $D(i-4)$ $D(i-5)$
 $C[15]$ $C[14]$ $C[13]$ $C[12]$ $C[11]$ $C[10]$ bits

The bits with index 0 to 4 are then used again in that order, shifting in to the coder 40 from the left with
 35 extraction of a bit quadruple after every shift. After these five last shifts the encoder memory 42 contains:

D(i)	D(i-1)	D(i-2)	D(i-3)	D(i-4)	D(i-5)	
C[4]	C[3]	C[2]	C[1]	C[0]	C[64]	bits

Thus, after one further shift the state of the encoder 40 will have returned to the starting state. The data bits can be visualized as being stored in a 16-stage circular buffer which is rotated one revolution so that every bit successively appears in the position corresponding to D(i-5).

The fields are presented to the DTX Trailer convolutional encoder 42 in the order starting from the signaling word header. Bits within a field are presented to the coder 42 in the order of most significant bit (MSB) first. Each word is formatted as shown in Fig. 3D.

The 8-bit message field was described above. The 8 data bits of the message field in the DTX Trailer word is appended with the 8-bit CRC to detect the presence of channel errors in the data, as well as to provide a mechanism for distinguishing the DTX Trailer data from speech data. For explanatory purposes, one method of differentiating between speech blocks and DTX Trailer blocks is to utilize the information present in the respective CRC fields.

Referring to Fig. 6, this invention thus provides a method for operating the mobile station 10, and includes the steps of, prior to transmitting a burst in a last frame before entering a discontinuous transmission (DTX) mode, generating a message word that indicates that the mobile station is about to enter the DTX mode (Block A); using a predetermined generator polynomial to produce an error detection word from the message word (Block B); and combining the message word and the error detection word into a DTX Trailer word (Block C), having a format shown in Fig. 3D. The method further includes the steps of

convolutionally encoding the DTX Trailer word (Block D); interleaving the DTX Trailer word with a speech or a signalling word, as in Fig. 4 (Block E); and transmitting the interleaved DTX Trailer word to the BMI 32 (Block F).

5 In a further aspect this invention provides an improved technique to transmit CN parameters to the base station 30, by using the MAHO FACCH message train. More particularly, and for the system specified by EIA/TIA IS-136 parts 1 and 2 (and similar systems), a preferred approach is to utilize
10 the available 130 bits at the beginning and end of the MAHO FACCH message train. This is accomplished by sending the latter half of 260 bits in the 130 unused bits of the first FACCH slot position, and the former half in the 130 unused bits of the last FACCH slot in the MAHO FACCH message
15 train. For the last slot before entering the DTX_Low State, the unused 130 bits can be changed to use a different intra-slot interleaving, e.g., 1/4 rate convolutional coding employed for the regular FACCH messages. Using the 1/4 rate convolutional coding and a
20 16-bit FACCH CRC, the result is 16 usable bits. One value of this 16-bit field is defined to indicate the beginning of the DTX_Low State to the base station 30.

An alternative method uses these additional bits with any suitable channel coding to carry any other control
25 information to the base station 30.

While it is also possible to change the interleaving of the intermittent MAHO FACCH Message train, this approach is not as effective, and may create a problem when the DTX_High State is entered immediately after the MAHO FACCH Message
30 Train.

The preferred method can be used in any system employing an interleaved Traffic Channel within a DTX system, such as

GSM.

In greater detail, the method uses a modified Abbreviated Slot, which may be sent in all assigned mobile station slots when in the DTX_Low State. As the network allows, the base station 30 may enable the mobile station 10 to gradually terminate the transmission of Abbreviated Slots. This is controlled by an optional information element in, by example, the Digital Traffic Channel Designation, Handoff and Physical Layer Control Messages. This optional information element gives a count of mobile station transit slots that can be skipped by the mobile station 10. At least two bits are dedicated for this purpose, although the use of more bits gives greater control.

The Abbreviated Slot as used herein does not carry any control information from the mobile station 10 to the base station 30 so as to enable the gradual upgrade of the system to full DTX operation. All control information (e.g., MAHO results and CN Parameters) are carried instead by FACCH messages.

The DTX Skip Length information element (two bits) can indicate the Abbreviated Slot TX requirement in the manner shown below:

Description	Code
send Abbreviated Slot at every assigned slot	00
send Abbreviated Slot at every 4th slot	01
send Abbreviated Slot at every 16th slot	10
no Abbreviated Slot required	11

Abbreviated Slot Format

6 bits	28 bits	12 bits	6 bits
R	SYNC	CDVCC	R

Note that the timing of this slot is delayed eight symbols to align it with adjacent slot synchronization bits in the TDMA Frame. With the ramp-up and ramp-down bits (R) the length of the Abbreviated Slot is 52 bits. If desired, a short (3 symbol) preamble having, for example, bits 101010 can be added.

When the mobile station 10 is in the DTX_Low State, sending the MAHO FACCH messages at a rate specified by the base station 30 (for example, at 0.5 or 1 second intervals), the two slot interleaving causes 130 bits to be unused both in the beginning and end of the message train. These unused bits are utilized, in accordance with an aspect of this invention, by reversing the order of x-bits and y-bits sent in the interleaved CN Parameter Message, and sending the MAHO FACCH message train in a regular manner (see Section 2.1.3.3.4 of IS-136.2) Using this method, one full slot transmission can be saved, resulting in greater savings in the mobile station DTX_Low CN-transmission. With a 0.5 second CN update interval, and if there is more than one channel quality measurement (CQM) to be sent, the messages can be arranged such that the first CQM is sent together with the CN parameters. In this way the CQM can always utilize the unused interleaver bits over at least two slots of interleaving. In the event that there is only one CQM message, and the CN parameters are transmitted at the 0.5 second interval, and every other CQM message is sent in a single TDMA slot. In this case the intra-slot interleaving is utilized.

In the DTX-Low state the transmitter 14 either remains off, and the CDVCC is not sent except for the transmission of FACCH messages, or, in accordance with this invention, Abbreviated Slots are transmitted at intervals defined by the above-defined DTX Skip Length parameter. All SACCH messages to be transmitted by the mobile station 10 in the

DTX_Low state are sent instead as a FACCH message, after which the transmitter 14 is returned to the off state, unless DTX has been otherwise inhibited.

5 Using this technique it is estimated that the battery savings during the DTX_Low state can be improved by about 20% to 30%, depending on how many FACCH slots are used for MAHO transmission.

10 Based on the foregoing it can be realized that this invention teaches a method and system for formulating a message to indicate that the mobile station 10 is about to enter the DTX_Low state, and that then interleaves this message with unused bits of a last message transmitted before entering the DTX_Low state. By receiving the message, the base station 30 is able to obtain knowledge of
15 the mobile station 10 entering the DTX_Low state.

20 This invention thus utilizes free bits due to an existing interleaving scheme. In interleaving the information of one logical frame is spread over two physical frames. When the mobile station 10 detects a silent moment in speech (e.g. based on information from a voice activity detector (VAD) function), the mobile station 10 begins to transition into the DTX_low state. At the end of all hangover slots and CN parameters there are, due to interleaving, some number (e.g., 130) of unused bits. These bits can be used,
25 in accordance with an aspect of this invention, to notify the BMI 32 that the mobile station 10 has entered the DTX_Low state.

30 While the mobile station 10 is in the DTX_Low state (typically transmitting CQM results and CN parameters), it again has unused bits both at the beginning and at the end of CQM results (sent on FACCH). In this case the mobile station 10 uses the free bits to send CN parameters (or a

single frame of any FACCH message) so that half of the bits (e.g., 130) are sent in advance in the unused portion of the starting FACCH burst. In this case the heading and trailing parts of the frame are only a few slots away from one other.

In general, this invention teaches the use of otherwise unused slots that, due to interleaving, happen to be part of mobile-transmitted bursts, either while entering the DTX_Low state or while in the DTX_Low state. This invention teaches the use of these unused (free) bits for 1) sending channel quality information, 2) CN parameters, and/or 3) the DTX Trailer Word information. In principle any control type of information can be sent in either case, i.e., when entering the DTX_Low state and when in the DTX_Low state.

As one further example of the utility of this invention, if an internet connection is active in the mobile station 10, and the mobile station 10 is transmitting only very little data on the reverse link (e.g., only a keystroke that is occasionally entered by the user), while the forward link is being heavily utilized to download information (e.g., to download web pages), the reverse link keystroke data can be interleaved with the messages required to be sent during the DTX_Low state (typically CQM).

Unused bits can be utilized so that the first part of a particular information frame (e.g. a CN parameters frame) is transmitted using the unused portion of the last normal length burst at the time mobile station 10 enters the DTX_Low state, and the next part of the particular information frame is transmitted after, by example, 0.5 or 1.0 second, when the next CQM message is transmitted.

In general, the teaching of this invention applies as well

to a mobile station operating the Data mode, such as when a circuit switched data connection specified by IS-130 and IS-135 is used. In this case there is a possibility for the mobile station 10 to not transmit slots if only null slots are available for transmission. This may occur when the internet is accessed, since the mobile station 10 may only occasionally send HTML codes to the network server, while the network server sends a significant amount of data to the mobile station 10. In the case of such a circuit switched connection there is no need to send CN data or hangover slots to the BMI 32, and the power savings are increased. It may also be beneficial for network to obtain information as to when the mobile station 10 enters the DTX_Low state. The user generated HTML strings can be sent with the MAHO information using the available free bits in the beginning and ending slots.

By applying a more optimal channel coding scheme in accordance with an aspect of this invention the information can be sent as reliably as when using the normally specified interleaving scheme.

The power saving effect results directly from using the free bit capacity that previously has been unused. By example, the transceiver of the mobile station 10 can be shut off earlier than would be possible without the use of this invention.

Although described in the context of preferred embodiments, it should be realized that a number of modifications to these teachings may occur to one skilled in the art.

By example, and as was stated, the teaching of this invention can be employed to send any type of desired information from the mobile station 10 to the base station 30, and is not limited to sending only CN parameters and/or

CQM in an unused portion of a frame. Furthermore, the teachings of this invention can also be applied when transitioning from the DTX_Low to the DTX_High states, in IS-136 and GSM systems by example, as unused frame capacity
5 will also be present due to interleaving.

Thus, while the invention has been particularly shown and described with respect to preferred embodiments thereof, it will be understood by those skilled in the art that changes in form and details may be made therein without departing
10 from the scope and spirit of the invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
220